


K641LX LCD Keypad Installation Notes

P ▲ R ▲ D O X™



Overview

- Product Description
- Compatibility
- Product Specifications

Product Description

The K641LX is an LCD keypad with built-in transceiver. The K641LX simplifies the installation of a Paradox wireless system by eliminating the need for a separate transceiver (RTX3). This approach reduces system costs and simplifies installation. Considering that keypads are typically installed near entry doors, the K641LX also ensures optimal RF performance range for remote controls. Besides its wireless capability, the K641LX offers the same features as the K641 and the same wireless expansion of the RTX3.

Compatibility

As part of the Digiplex EVO family of products, the K641LX is currently compatible with the EVO192 control panel.

Always visit paradox.com/compatibilitychart for the latest list of compatible panels.

NOTE: EVO48 is integrated with the EVO192 control panel.

Product Specifications

- Built-in transceiver (433 or 868 MHz)
- 32-character, blue LCD with programmable labels
- Power: 12 to 14 Vdc
- Current consumption: 120 mA (maximum)
- Real-time zone alarm display
- In-field firmware upgradable via CV4USB and WinLoad
- 1 addressable zone output
- 1 PGM output
- 14 one-touch action buttons
- 3 keypad-activated panic alarms
- Display time using the 12 or 24 hr. format
- Adjustable backlight, contrast, and scroll speed
- Independently set chime zones
- Connects to 4-wire combus

© 2011 Paradox Ltd. All rights reserved.
Specifications may change without prior notice.
For complete patent, trademark, certification, and warranty information, please visit www.paradox.com.